

I2C Jumpers			Address		
ad2	ad1	ad0	Binary	Hex	Dec
0	scl	0	0010_0000	0x10	16
0	scl	1	0010_0001	0x11	17
0	sda	0	0010_0010	0x12	18
0	sda	1	0010_0011	0x13	19
1	scl	0	0010_0100	0x14	20
1	scl	1	0010_0101	0x15	21
1	sda	0	0010_0110	0x16	22
1	sda	1	0010_0111	0x17	23
0	scl	scl	0011_1000	0x18	24
0	scl	sda	0011_1001	0x19	25
0	sda	scl	0011_1010	0x1A	26
0	sda	sda	0011_1011	0x1B	27
1	scl	scl	0011_1100	0x1C	28
1	scl	sda	0011_1101	0x1D	29
1	sda	scl	0011_1110	0x1E	30
1	sda	sda	0011_1111	0x1F	31
0	0	0	0100_0000	0x20	32
0	0	1	0100_0001	0x21	33
0	1	0	0100_0010	0x22	34
0	1	1	0100_0011	0x23	35
1	0	0	0100_0100	0x24	36
1	0	1	0100_0101	0x25	37
1	1	0	0100_0110	0x26	38
1	1	1	0100_0111	0x27	39
0	0	scl	0101_1000	0x28	40
0	0	sda	0101_1001	0x29	41
0	1	scl	0101_1010	0x2A	42
0	1	sda	0101_1011	0x2B	43
1	0	scl	0101_1100	0x2C	44
1	0	sda	0101_1101	0x2D	45
1	1	scl	0101_1110	0x2E	46
1	1	sda	0101_1111	0x2F	47
scl	scl	0	1010_0000	0x50	80
scl	scl	1	1010_0001	0x51	81
scl	sda	0	1010_0010	0x52	82
scl	sda	1	1010_0011	0x53	83

sda	scl	0	1010_0100	0x54	84
sda	scl	1	1010_0101	0x55	85
sda	sda	0	1010_0110	0x56	86
sda	sda	1	1010_0111	0x57	87
scl	scl	scl	1011_1000	0x58	88
scl	scl	sda	1011_1001	0x59	89
scl	sda	scl	1011_1010	0x5A	90
scl	sda	sda	1011_1011	0x5B	91
sda	scl	scl	1011_1100	0x5C	92
sda	scl	sda	1011_1101	0x5D	93
sda	sda	scl	1011_1110	0x5E	94
sda	sda	sda	1011_1111	0x5F	95
scl	0	0	1100_0000	0x60	96
scl	0	1	1100_0001	0x61	97
scl	1	0	1100_0010	0x62	98
scl	1	1	1100_0011	0x63	99
sda	0	0	1100_0100	0x64	100
sda	0	1	1100_0101	0x65	101
sda	1	0	1100_0110	0x66	102
sda	1	1	1100_0111	0x67	103
scl	0	scl	1101_1000	0x68	104
scl	0	sda	1101_1001	0x69	105
scl	1	scl	1101_1010	0x6A	106
scl	1	sda	1101_1011	0x6B	107
sda	0	scl	1101_1100	0x6C	108
sda	0	sda	1101_1101	0x6D	109
sda	1	scl	1101_1110	0x6E	110
sda	1	sda	1101_1111	0x6F	111